



Features Usage Guide

gTalk® Home Phone Service

gTalk® Home features usage guide

Feature	Dial	Purpose
Caller ID Blocking	*31	To block Caller ID for all calls.
	*32	To cancel Caller ID Block for all calls. <i>Note: Also you may enable Caller ID Blocking by login on to your account panel.</i>
Caller ID Blocking	*67 + number	To block Caller ID of specific telephone number only.
	*82 + number	To cancel blocked Caller ID of specific telephone number only.
Last-Call Return	*69	To return call to the last incoming call.
Do Not Disturb	*78	To set DnD (Do Not Disturb) feature.
	*79	To cancel DnD. <i>Note: Also you may enable this feature by login on to your account panel.</i>
Anonymous Call Block	*77	To block anonymous calls.
	*87	To cancel anonymous call block. <i>Note: Also you may enable this feature by login on to your account panel.</i>
Selective Call Blocking	*60 + number	To add a specific telephone number to block list.
	*80 + number	To delete a specific telephone number from block List. <i>Note: Also you may configure this feature by login on to your account panel. You may Add/Edit/Delete any number which you want to block/unblock.</i>
Call Forwarding	*70 + number	To forward calls to a specific telephone number on Ring-Timeout.
	*71 + number	To forward calls to a specific telephone number when reachable.
	*72 + number	To forward all incoming calls to a specific telephone number for any reason.
	*73	To cancel any Call Forwarding instruction. <i>Note: Also you may configure your Call Forwarding feature by login on</i>

		<i>to your account panel.</i>
--	--	-------------------------------

CallForwarding

Activating Call Forwarding: You may activate Call Forwarding feature whenever you want your calls to be sent to another phone, including a mobile phone. Once activated, all your calls will be sent to the forwarded number you request.

Dial *70 + Number - To forward calls to a specific telephone number after Ring-Timeout.

Dial *71 + Number - To forward calls to a specific telephone number when unreachable.

Dial *72 + Number - To forward all incoming calls to a specific telephone number for any reason.

Deactivating Call Forwarding: Turn Call Forwarding off when you want to receive calls at your home phone.

Dial *73 - To cancel any Call Forwarding instruction.

Note: Also you may configure your Call Forwarding feature by login to your account panel.

gTalk®HomeVoiceMail

To activate Voice Mail – Login to your gTalk® Home account and activate it.

To setup Voice Mail first dial 101. Thereafter do the followings:

- To listen new messages press 1
- To listen old messages press 2
- To record/delete personal greetings press 3

Note: If there is any Voice Mail in your mailbox you will be notified by the following MWI (Message Waiting Indication):

- On picking up the receiver you will hear dial tone starting with 4 stutter (braking) tone
- Telephone/Cordless set light may turn on (depending on phone set)
- An envelope icon may appear on phone screen (depending on phone set)

CallWaiting

This feature lets you know when another caller is trying to reach you while you're on another call. You will hear a short tone.

To receive 2nd call press FLASH (first caller on hold)
Back (toggle/swap) to the first caller press FLASH

3-WayCalling(Conference)

To make 3-way calling (conference)

Dial or receive a call
Press **FLASH** to get the dial tone
Dial 2nd number
Press **FLASH** to connect 3-Way Calling (conference)

SpeedDial

gTalk® Home provides 99 (1-99) Speed Dial facility. To set speed dial

Login to your gTalk® Home account
Go to Speed Dial under User Menu
Follow onscreen instructions to Add/Edit/Delete Speed Dial number.

CallerIDBlocking

You may block caller ID for all calls or specific telephone number by dialing as followings:

Dial *31 -- To block Caller ID for all calls.
Dial *32 -- To cancel Caller ID Block for all calls.

Dial *67 + number -- To block Caller ID for this call only.
Dial *82 + number -- When Caller ID is blocked, to pass Caller ID for this call only.

Note: Also you may enable Caller ID Blocking by login on to your account panel.

SelectiveCallBlocking

Dial *60 + number -- To add a specific telephone number to block list.
Dial *80 + number -- To delete a specific telephone number from block list.

Note: Also you may configure this feature by login on to your account panel. You may Add/Edit/Delete any number which you want to block/unblock.